

Portable Locator

Model No.: V07

User Manual



Thank you for choosing our product. For safe and optimal use of the device, please, read this guide carefully before getting started.

Warnings and safety instructions

- Please, do NOT take out the SIM card when the device is powered on. It could cause damage to the device.
- Keep the device away from fire and avoid high temperature environments.
- The device does not prevent data roaming. It can create expensive data traffic when used in a different country with the same SIM card.
- The device and the mobile app are continuously developed. Their functions and language can slightly differ from this manual. Use this document as a reference only.

1 Before you begin

- Make sure the device is fully charged before you start the installation. It is recommended to charge the device for at least 12 hours before the first use.
- The device comes with a quad band GSM chip (850/900/1800/1900 MHz) but it is recommended to ask your dealer which service operators support your device in your area.
- The device operates with a micro SIM card. Normal SIM cards cannot be inserted and nano SIM cards will damage the device which will result in losing the warranty.
- It is not possible to enter a PIN number with the device so make sure you use a SIM card that does not require a PIN number when inserted or remove the PIN security in a mobile phone before you insert it in the device.

1

2 Charging the device

Remove the device and the charging cable from the packaging. Connect the magnetic head of the cable to the metallic contacts on the back of the device (rotate the connector until the magnets pull it in position) and connect the other end of the cable to a USB power source.



Charging the device to its full capacity normally takes 2-3 hours. you can see a red led flashing continuously when charging ,once charging fully,will stop flashing .

However, for the first time, please, charge the device for 12 hours and 8 hours for the second and third times to ensure a long battery life.

3. The device (for the User which use the device)

Below you will find the description and operation of the device.



2

Note: Make sure when use the device, the GPS antenna does not point to the ground. Point to the sky, GPS signal will be the best.

3.1 Powering on

- Before turning on the device, use screw driver to open the SIM card slot cover and insert the micro SIM card as shown on the picture.



- Push far inside until you hear the spring mechanism locking the card.
- Close the SIM card slot cover and make sure it has been pushed into place tightly in order to avoid water entering the watch.

Note: after you insert the sim card and turn on the device, you will see led change colour red-blue-green-red, (means device detecting the sim card)

Wait 1-2 minutes and press button to see led color,in normal ,led will change from red to blue/green color, if led is off, the device may not support your telecom operator. please contact the distributor to check with your sim card APN setting.In future using, if press button and see led being off, you might have run out of your data package or the coverage is not enough for data transfer.(not exclude the device powering off)

3

3.2. Buttons

- **Button 1: On/Off / SOS**

(1)Power on the device
After insert the micro sim card, hold the button more than 3 seconds will power on the device.

If detect the sim card successfully, can see the Led changes from red-blue-green-red.

Wait unit see Led in blue or green color, if device connect with server and under wifi/LBS positioning, will show blue color;if device under gps positioning, Led will show green color. (**Note:** for power saving .Led will off. press button to see led color)

(2)Make SOS calling from the device

After the guardian added the device on app,and for device ,after you see the led in blue or green color , hold the button more than 3 seconds , you will hear a buzzer sound, and the device will call first 4 phone numbers in the contact list in turn for 3 times.Hold the button more than 3 seconds to cancel the calling.

(3)Answer the call

Press the button to answer the call.When talking finished, hold the button more than 3 seconds to hang up the calling.

3.3 Powering off the device

- If there is no SIM card in the device: press and hold Button to turn off the device.

4

- When there is a SIM card in the device: for safety reasons, the device can only be turned off remotely. Go to application -main menu Manage-Remote device turn off function.

Note: only the administrator can turn off the device from the APP.

4. Operating the mobile application

With micro sim card installed in device and device powered on, wait till see the led in blue/green color, now you can start using the application. Please, follow the steps below.

4.1 Downloading the mobile application

Please, search for and install one of the following software:

- For Apple phones, search for “TAKIT GPS PRO” in the App Store.
- For android phones, search for “TAKIT GPS PLUS” in the Google Play store.
- Allow pushing notification function on your phone

Once the software is installed,

Note: on your mobile phone settings-notifications-TAKIT GPS PRO should turn on all the buttons of allow notifications as below:



5


4.2 Registering a user and logging in

- Tap **new user** to start the registration process.
- Select **Mobile** or **Email** to create your user account.
- If you select **Mobile**, the verification code will be sent to you in an SMS message to the given phone number. This number will be one of the registered phone numbers that can communicate with the device.

Note: in countries where the local mobile number starts with a zero (0), please, register with an email address. The verification code cannot be sent to these kinds of phone numbers.

- If you select **Email**, the verification code will be sent to you in an email.

Note: if you do not receive the email with the verification code, please, check your spam box or spam quarantine.




4.3 Setting up the application (connecting to a device)

Once you are logged in the mobile app, do the following to connect it to the device:

6

1. Tap  to register your device.



2. There are two ways to register the device. Either by scanning its QR code or by manually entering its CID:

- o **To scan the QR code:** Tap the middle of the screen to start the camera (allow using the camera if asked). Now scan the QR code that is on the back of your device or on the outside of its packaging. Move the QR code towards or away from the phone until it is read automatically.

- o **To enter the CID number:** Tap enter CID, type in the CID number and then tap OK.

3. On the next screen, select the female/male/type
4. Enter the name of device wearer and phone number on the SIM Card that you will insert into the device. Tap next.
5. Select your relation to the user. Tap done.

Note: the user who first links its phone to the device will become the administrator of that device. This can be changed later.

4.4 Main functions


The following section is a brief description for mobile APP.


4.4.1 Map screen

The Map screen shows the location of the linked devices on the map as well as provides ways of communication between the app and any of those devices.

The Map screen is also the first screen you see when you start the software.


When started, the software shows all connected devices on


the map. You can slide head image  to select any of the devices to communicate with.



The software uses Google Maps to locate the devices. To better understand the location of the devices, you are offered three map visualization modes: Satellite, 2D and 3D. Tap  to switch between these options.

Warning: choosing Satellite mode may result in excessive data use in your mobile phone.

4.4.2 Main Menu:



- Tap map to enter the map page, Tap  to see the current location of the device. This will only work if the device is turned on with an inserted SIM card; the SIM card has sufficient data.

- Tap  to see a sequence of previous locations of the device. Tap  to choose a period of time to display.

- Tap  to change the application language and check the application version

- Tap  to choose call or monitor device

4.4.2.1 Call and Monitor

Tap **call** to start a phone call, Tap **Monitor** to listen the device. On the Monitor mode, the device will automatically pick up the call without making a sound. This allows the guardian to listen into the device environment without being noticed.

4.4.2.2 Alerts


Tap **Message** to jump to the messages screen. When there is an incoming message for the device, or alerts for SOS, low battery, Enter/Exit Geo-fences, Change of administrator's rights etc, a red dot will appear on the icon **Message**. Tap to check new messages or alerts.

4.4.3.3 Contacts and administrator

Tap **Contacts** to see the list of phones and users linked to the device. The administrator of the device is displayed at the top. The administrator can add, modify

or delete any family member in the list and transfer the administration right to Backup administrator. Administrator can add contacts phone number even the numbers were not of accounts that registered in the APP.

4.4.3.4 Manage Device setting

Tap  to set up other device parameters or initiate additional functions:

(1) **Device user information:** Tap the name next to Avatar takes you to edit page of name, phone number of device etc.

(2) Tap **Manage Fence list:**

Tap **Fence list** to check or set up geo-fences. You can set up multiple geo-fences of rectangular or circular shape.

(3) **Mute:** You can set up multiple time intervals when the device will remain silent even if there is an incoming call or message.

(4) **Location mode:** You can choose between two options:

- **Smart mode:** the device location is updated every minute when the device is moving outside.
- **Manual mode:** the location will only be updated when you tap the **Loc** button on the Map screen.

Note: Automatic mode uses more battery.


(5) **Remote device turn off:** If a SIM card is inserted, the device can only be turned off remotely from the app by administrator, before doing this in APP, an automatic device power on time can be set.

(6) **Device alarm:** Set up alarms to wake up or remind the device user to do something.

(7) **Device time:** Set the correct date and time of the device remotely.

(8) **Device tracking:** This function will help you locate the device by instructing the device to play a loud sound effect. Press any button on the device to silence it.

(9) **Volume:** Adjust the volume of sound alerts and phone calls separately.

(10) **Restore factory setting:** Tap  at top right corner to see "Restore factory settings", when confirmed, all contact list of device will be cleared.
Note: only Administrator can use this function.

5 FAQ

Please, find the most often asked questions and their answers below.

(1) I cannot turn on the device

The battery in your device might have run out of power. Please, connect the device to a power source until fully charged and then try again.

(2) I cannot scan the QR code

The following methods can help your phone read the QR code:

- If the ambient light is low, move to a brighter area and retry scanning the QR code.
- Try adjusting the distance between the QR code sticker and the camera of the phone so that the auto focus can make a sharp picture and the QR code is large enough to reveal its details.

(3) What operation systems is the APP compatible with?

The mobile application is compatible with iOS devices running iOS7.0 or newer operating systems and android devices running android 4.0 or newer.

(4) How to transfer the administration right to another person?

Only the administrator can transfer this right.

1. Open the mobile application.
2. Log on as the administrator of the watch.
3. Open the **Master list** of the selected device in the Main menu.
4. Tap and hold one of the Backup administrators.
5. Tap **Transfer Administration Rights** in the popup menu.

Note: only Backup administrators can receive the administrator right. Other added phone numbers cannot.

(5) How to delete a previously added phone number?

Only the administrator can delete phone numbers.

1. Open the mobile application.
2. Log on as the administrator of the device.
3. Open the **master list** of the selected device in the Main menu.

4. Tap and hold one of the numbers in the list.
5. Tap **Delete** in the popup menu and confirm your choice.

Please reset the device before offering the device to a new user, otherwise, the first caregiver of new user could not become administrator.

(6) How to prevent other people from adding the device to their phone?

As the administrator of the device, you can keep others from extending the Family list.

1. Open the mobile application.
2. Log on as the administrator of the device.
3. Open the **master list** of the selected device in the Main menu.
4. Tap the gear button near the bottom right corner.
5. Tap the switch next to **Allow guard** to disable this feature.